




MOC3020 MOC3021 MOC3022 MOC3023

PACKAGE DIMENSIONS







Equivalent Circuit

DESCRIPTION

The MOC3020, MOC3021, MOC3022 and MOC3023 are optically isolated triac driver devices. These devices contain a GaAs infrared emitting diode and a light activated silicon bilateral switch, which functions like a triac. This is designed for interfacing between electronic controls and power triacs to control resistive and inductive loads for 240 VAC operations.

FEATURES

- Excellent I_{FT} stability—IR emitting diode has low degradation
- High isolation voltage—minimum 7500 VAC peak
 Underwriters Laboratory (UL) recognized—File #E90700

APPLICATIONS

- European applications for 240 VAC
- Triac driver
- Industrial controls
- Traffic lights
- Vending machines
- Motor control
- Solid state relay

ST1603

| ABSOLUTE MAXIMUM RATINGS | | | | |
|------------------------------------|--|--|--|--|
| TOTAL PACKAGE Storage temperature | INPUT DIODE Forward DC current 50 n Reverse voltage 3 Peak forward current (1 μs pulse, 300 pps) Power dissipation (25°C ambient) 100 m Derate linearly (above 25°C ambient) 1.33 mW/ | | | |
| | OUTPUT DRIVEROff-state output terminal voltage 400 Volts On-state RMS current $T_A=25^{\circ}\text{C}$ 100 mA (Full cycle, 50 to 60 Hz) $T_A=70^{\circ}\text{C}$ 50 mA Peak nonrepetitive surge current 1.2 A (PW=10 ms, DC=10%) 1.2 Ns 1.2 Ns Total power dissipation (25°C ambient) 1.2 Ns 1.2 Ns Derate above 1.2 Cs 1.2 Ns 1.2 Ns | | | |



ELECTRO-OPTICAL CHARACTERISTICS (25°C Temperature Unless Otherwise Specified)


| CHARACTERISTIC | SYMBOL | MIN. | TYP. | MAX. | UNITS | TEST CONDITIONS |
|---|----------------------------|------|------|------|-------|---------------------------------|
| INPUT DIODE Forward voltage | $V_{\scriptscriptstyle F}$ | | 1.2 | 1.50 | V | I _F =10 mA |
| Junction capacitance | C, | - | 50 | | pF | V _F =0 V, f=1 MHz |
| Reverse leakage current | I _R | | | 100 | μΑ | V _R =3.0 V |
| OUTPUT DETECTOR Peak blocking current, either direction | I _{DHM} | _ | 10 | 100 | nA | V _{DRM} =400 V, Note 1 |
| Peak on-state voltage, either direction | V _{TM} | _ | 2.5 | 3.0 | Volts | I _™ =100 mA Peak |


| DC CHARACTER | ISTICS | SYMBOL | MIN. | TYP. | MAX. | UNITS | TEST CONDITIONS |
|---|-------------------|-----------------|------|------|------|---------------|-------------------------------------|
| LED trigger current (current required MOC3020 | l _{FT} — | _ | _ | 30 | mA | Main terminal | |
| MOC30 | MOC3021 | I _{FT} | | _ | 15 | mA | voltage=3.0 V, R _L =150Ω |
| | MOC3022 | I _{FT} | _ | _ | 10 | mA | _ |
| | MOC3023 | I _{FT} | _ | _ | 5 | mA | |
| Holding current | | I _H | _ | 100 | _ | μΑ | Either direction |

| CHARACTERISTICS | SYMBOL | MIN. | TYP. | MAX. | UNITS | TEST CONDITIONS |
|---|--------|------|------|------|-------|---|
| dv/dt RATING Critical rate of rise of off-state voltage | dv/dt | _ | 12 | _ | V/μs | Static dv/dt, T _A =85°C (see Fig. 3) |
| Critical rate of rise of commutating voltage | dv/dt | _ | 0.2 | _ | V/μs | Commutating dv/dt I _{LOAD} =15 mA (see Fig. 4) |

| ISOLATION CHA | RACTERIS | STICS | | | | |
|-----------------------|------------------|-------|------|------|----------------------|-----------------------------------|
| CHARACTERISTICS | SYMBOL | MIN. | TYP. | MAX. | UNITS | TEST CONDITIONS |
| Isolation voltage | V _{iso} | 5300 | | | V _{AC} RMS | I _{ι-0} ≤1 μA, 1 Minute |
| | V _{iso} | 7500 | | - | V _{AC} PEAK | l _{i-0} ≤ 1 μA, 1 Minute |
| Isolation resistance | R _{iso} | 1011 | | | ohms | V _{I-O} =500 VDC |
| Isolation capacitance | C _{iso} | | 0.5 | | pF | f=1 MHz |

Note 1: Ratings apply to either polarity of pin 6 — referenced to pin 4. Voltages must be applied within dv/dt rating.







DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

- Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
- A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.